

Application No.: 10/608,612
February 22, 2005
Page 2 of 8

Amendments to the Specification

Line 9 to line 29 on page 3 have been amended to read as follows:

Referring now to the first current path I_A , the current source transistor M_1 ~~is a PMOS transistor having~~ has a source terminal coupled to a supply signal V_{DD} , a drain terminal coupled to a feedback control node A, and a gate terminal coupled to a central node B. The feedback transistor M_4 is an NMOS transistor having a drain terminal coupled to the feedback control node A, a source terminal coupled to a ground node, and a gate terminal coupled to a current mirror node C.

Referring now to the compensation current path I_B , the first resistor R_1 is coupled between the supply signal V_{DD} and the central node B. The feedback control transistor M_3 is a PMOS transistor having a source terminal coupled to the central node B, a drain terminal coupled to the current mirror node C, and a gate terminal coupled to the feedback control node A. The feedback-generating transistor M_5 is an NMOS transistor having a source terminal coupled to the ground node, a drain terminal coupled to the current mirror node C, and a gate terminal also coupled to the current mirror node C.

Referring now to the second current path I_C , the output transistor M_2 is a PMOS transistor having a source terminal coupled to the supply signal V_{DD} , a drain terminal coupled to an output node V_{REF} , and a gate terminal coupled to the central node B. The thermal coupling transistor M_6 ~~is an NMOS transistor having~~ has a source terminal coupled to the ground node, and both a drain terminal and a gate terminal coupled to the output node V_{REF} . The second resistor R_2 and the output capacitor C_1 are coupled between the output node V_{REF} and the ground node, such that the second resistor R_2 and the output capacitor C_1 are in parallel with the gate-source and drain-source voltages of the thermal coupling transistor M_6 .